

Product data sheet

Specifications

SQUARE D



Meter accessory, EZ Meter-Pak, bus extension, 1 phase, 1200A bus, 6in W

EZM1EXT6

Product availability: Stock - Normally stocked in distribution facility

Main

Device short name	EZ
Range of Product	Meter-Pak

Complementary

Line Rated Current	1200 A
[Ue] rated operational voltage	120/240 V AC
Bus rated current	1200 A
Device mounting	Surface
Enclosure Material	Steel
Number of Phases	1 phase
Product Certifications	UL Listed
Height	11.66 in (296.16 mm)
Width	19.34 in (491.24 mm)
Depth	6.37 in (161.80 mm)

Environment

Enclosure Rating	NEMA 3R
------------------	---------

Ordering and shipping details

Category	US10DE400027
Discount Schedule	0DE4
GTIN	785901889892
Returnability	Yes
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	7.30 in (18.542 cm)
Package 1 Width	14.40 in (36.576 cm)
Package 1 Length	21.00 in (53.34 cm)
Package weight(Lbs)	19.831 lb(US) (8.995 kg)

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Contractual warranty

Warranty

18 months



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint	
Carbon footprint (kg CO2 eq, Total Life cycle)	552
Environmental Disclosure	Product Environmental Profile

Use Better

Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Compliant with Exemptions
REACH Regulation	REACH Declaration
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

Repack and remanufacture	
Circularity Profile	No need of specific recycling operations
Take-back	No