

# Product data sheet

Specifications

SQUARE D



## Meter accessory, EZ Meter-Pak, bus outside corner section, 1200A bus, single phase

EZM1ELBOW

**Product availability: Non-Stock - Not normally stocked in distribution facility**

### Main

Device short name	EZ
Range of Product	Meter-Pak

### Complementary

Line Rated Current	1200 A
[Ue] rated operational voltage	120/240 V AC
Bus rated current	1200 A
Device mounting	Surface
Enclosure Material	Steel
Number of Phases	1 phase
Product Certifications	UL Listed
Height	19.5 in (495.3 mm)
Width	14.46 in (367.28 mm)
Depth	14.46 in (367.28 mm)

### Environment

Enclosure Rating	NEMA 3R
------------------	---------

### Ordering and shipping details

Category	US10DE400027
Discount Schedule	0DE4
GTIN	785901295327
Returnability	No
Country of origin	MX

### Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	19.5 in (49.5 cm)
Package 1 Width	14.4 in (36.7 cm)
Package 1 Length	14.4 in (36.7 cm)
Package weight(Lbs)	47.999 lb(US) (21.772 kg)

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

# Contractual warranty

---

Warranty

18 months


## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better

 <b>Materials and Substances</b>	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
<a href="#">EU RoHS Directive</a>	Compliant with Exemptions
REACH Regulation	<a href="#">REACH Declaration</a>
California proposition 65	<b>WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to <a href="http://www.P65Warnings.ca.gov">www.P65Warnings.ca.gov</a></b>

### Use Again

 <b>Repack and remanufacture</b>	
Take-back	No