

# Product data sheet

Specifications

SQUARE D



Main lugs unit, EZ Meter-Pak,  
400A, 240VAC max, 3ph/4W,  
800A bus, OH/UG, Type 3R, Cu  
bus

EZM3400TBCU

Product availability: Stock - Normally stocked in distribution facility

## Main

Device short name	EZ
Main Type	Main Lugs
Range of Product	EZ meter-pak

## Complementary

Bus rated current	400 A
Device mounting	Surface
Electrical connection	Lugs, line side
Enclosure Material	Steel
Material	Copper: busbar
Product Certifications	UL Listed
Height	30.46 in (773.68 mm)
Width	17.15 in (435.61 mm)
Depth	7.09 in (180.09 mm)

## Environment

Enclosure Rating	NEMA 3R
------------------	---------

## Ordering and shipping details

Category	US10DE400025
Discount Schedule	0DE4
GTIN	785901823421
Returnability	Yes
Country of origin	MX

## Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	8.20 in (20.828 cm)
Package 1 Width	21.00 in (53.34 cm)
Package 1 Length	31.20 in (79.248 cm)

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

---

Package weight(Lbs) 60.001 lb(US) (27.216 kg)

## Contractual warranty

---

Warranty 18 months

## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better

 <b>Materials and Substances</b>	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
<a href="#">EU RoHS Directive</a>	Compliant with Exemptions
REACH Regulation	<a href="#">REACH Declaration</a>
California proposition 65	<b>WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to <a href="http://www.P65Warnings.ca.gov">www.P65Warnings.ca.gov</a></b>

### Use Again

 <b>Repack and remanufacture</b>	
Take-back	No