

Product data sheet

Specifications

SQUARE D



Panelboard accessory, NQ, lug kit, feed thru, 225A, 54 circuits or higher

NQFTL2H

Product availability: Stock - Normally stocked in distribution facility

Main

Product Lug kit

Complementary

Number of circuits	84 72 54
Current Rating	225 A
Tightening torque	24.8...30.09 lbf.in (2.8...3.4 N.m) (AWG 1/0...350 kcmil)

Environment

Product Certifications cULus

Ordering and shipping details

Category	US1PE1A08332
Discount Schedule	PE1A
GTIN	785901508151
Returnability	Yes

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	5.3 in (13.5 cm)
Package 1 Width	9.3 in (23.6 cm)
Package 1 Length	13.1 in (33.3 cm)
Package weight(Lbs)	5.71 lb(US) (2.59 kg)
Unit Type of Package 2	PAL
Number of Units in Package 2	24
Package 2 Height	40.0 in (101.6 cm)
Package 2 Width	40.0 in (101.6 cm)
Package 2 Length	48.00 in (121.92 cm)
Package 2 Weight	137.04 lb(US) (62.16 kg)

Contractual warranty

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Warranty

18 months

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint

[Environmental Disclosure](#)

[Product Environmental Profile](#)

Use Better

Materials and Substances

Packaging made with recycled cardboard

No

Packaging without single use plastic

No

[EU RoHS Directive](#)

Compliant

REACH Regulation

[REACH Declaration](#)

California proposition 65

WARNING: This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

Repack and remanufacture

Circularity Profile

No need of specific recycling operations

Take-back

No