



GE
Lighting

26635 - Integrated 2ft LED Plastic Tubes

LED9ET8/2/835

- ☞ Convert your existing linear fluorescent fixture to LED lighting without needing a comprehensive reinstall.
- ☞ LED tubes are ideal for those seeking high energy savings with minimal installation time.
- ☞ Each LED tube is outfitted with an internal GE driver.
- ☞ GE integrated LED tubes run on electronic T8 instant-start or programmed start ballasts.
- ☞ Shatter resistant
- ☞ No UV
- ☞ Easy disposal, non-hazardous waste
- ☞ NSF Rated for food application (shatter resistant)
- ☞ UL Listed
- ☞ DLC Listed

Product Photo



GENERAL CHARACTERISTICS

Product Technology	LED
Rated Life (Hours)	50000 h
LED Tube Type	Plastic
Environmental Rating	LED_Tube_Plastic
10 Digit U	4316826635
Lamp Count	1
Life in Years	45.7 yr
Requested Structure	Carton
Estimated Energy Cost per Year	1.08
Bulb Shape	T8

PHOTOMETRIC CHARACTERISTICS

Rated Beam Spread	9 W
Initial Lumens-nominal	1100 lm
Color Temperature	3500 K

PRODUCT INFORMATION

Product Code	26635
Description	LED9ET8/2/835
Alternative Unit Of Measure	CASE
Standard Package Quantity	25
Ean UPC	043168266352
Standard Package GTIN	10043168266359
No Of Items Per Sales Unit	
No Of Items Per Standard Package	25
Sales Unit	Case
UCC	043168266352
Alternative Unit Of Measure	EACH
Standard Package Quantity	25
Ean UPC	043168266352
Standard Package GTIN	00043168266352
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	25
Sales Unit	Each
UCC	043168266352

DIMENSIONS

Bulb Max Overall Length-MOL	25.0 in
-----------------------------	---------

ELECTRICAL CHARACTERISTICS

Drive Current	45.7
Energy Efficiency Class	yr
Voltage <Nom>	120 V
Rated power (Watts)	9 W

CAUTIONS & WARNINGS

Caution

Risk of electric shock

Suitable for damp locations

Not intended for use with emergency exit fixtures or emergency exit lights

Risk of fire

Use only in place of fluorescent lamps specified on label

If the lamp or luminaire exhibits undesirable operation, immediately turn off power, remove lamp from luminaire and contact manufacturer

Direct replacement for 17W/24T8 lamps only

Do not install this lamp in a pre-heat luminaire

This lamp only operates on electronic ballasts

If lamp does not light when luminaire is energized, remove lamp from luminaire and contact lamp manufacturer or qualified electrician

