

Product data sheet

Specifications

SQUARE D



Meter accessory, EZ Meter-Pak, transition section, right, 1200A bus, single phase

EZM1TRANR

Product availability: Non-Stock - Not normally stocked in distribution facility

Main

Device short name	EZ
Range of Product	Meter-Pak

Complementary

Line Rated Current	1200 A
[Ue] rated operational voltage	120/240 V AC
Bus rated current	1200 A
Device mounting	Surface
Enclosure Material	Steel
Number of Phases	1 phase
Product Certifications	UL Listed
Height	23.25 in (590.55 mm)
Width	10.75 in (273.05 mm)
Depth	8.26 in (209.80 mm)

Environment

Enclosure Rating	NEMA 3R
------------------	---------

Ordering and shipping details

Category	US10DE400027
Discount Schedule	0DE4
GTIN	785901305835
Returnability	No
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	23.3 in (59.1 cm)
Package 1 Width	10.7 in (27.3 cm)
Package 1 Length	8.3 in (21 cm)
Package weight(Lbs)	38.200 lb(US) (17.327 kg)

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Contractual warranty

Warranty

18 months


Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.


[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

 Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Compliant with Exemptions
REACH Regulation	REACH Declaration
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

 Repack and remanufacture	
Take-back	No