


# Product data sheet

Specifications

SQUARE D



## Circuit breaker accessory, PowerPacT M/P/R, shunt trip, 24V AC/DC, 30VDC

S33659

Product availability: Stock - Normally stocked in distribution facility

### Main

Range of Product	PowerPact M PowerPact P PowerPact R
Product or Component Type	Coil
Device Application	Trips circuit breaker from remote location
Circuit breaker name	PowerPact M or P
Circuit breaker type	Standard

### Complementary

Rack type	Remote
Mounting Location	Inside the circuit breaker
Rated voltage	24...30 V DC

### Ordering and shipping details

Category	US10DE201250
Discount Schedule	0DE2
GTIN	785901612315
Returnability	Yes
Country of origin	US

### Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	1.500 in (3.810 cm)
Package 1 Width	2.500 in (6.350 cm)
Package 1 Length	4.300 in (10.922 cm)
Package weight(Lbs)	6.736 oz (190.962 g)

### Contractual warranty

Warranty	18 months
----------	-----------

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Environmental footprint

Carbon footprint (kg CO2 eq, Total Life cycle)	3
--	---

## Use Better

### Materials and Substances

Packaging made with recycled cardboard	Yes
--	-----

Packaging without single use plastic	Yes
--------------------------------------	-----

<a href="#">EU RoHS Directive</a>	Pro-active compliance (Product out of EU RoHS legal scope)
-----------------------------------	--

California proposition 65	WARNING: Cancer and Reproductive Harm - <a href="http://www.P65Warnings.ca.gov">www.P65Warnings.ca.gov</a>
---------------------------	--

## Use Again

### Repack and remanufacture

Circularity Profile	No need of specific recycling operations
---------------------	--

Take-back	No
-----------	----